



MOTWANE PRIVATE LIMITED



Central Broadcast System Components

Amplifiers



TK-PA Mixer Amplifier Series

- 3 MIC, 2 AUX inputs; 1 AUX output; 100V, 70V constant voltage and 4 ~16 Ohms speaker outputs; 5-element LED level meter
- Mute function for the insertion of urgent broadcast
- Independent gain, treble, and bass controls
- Output short-circuit protection and alarm
- Built-in 6-channel speaker selector

Model		TK-80P	TK-130P	TK-260P	TK-360P
Rated Power		80W	130W	260W	360W
Input	Line	< 200mv			
Sensitivity	Mic	< 5mv			
S/N Ratio	Line	> 70dB			
	Mic	> 66dB			
Output Mode		70V, 100V or 4-16Ω			
THD	Line	< 1%			
(1kHz)	Mic	< 1%			
Dimensions(H W L)		133×483×480mm			
Net Weight		12.2kg	12.8kg	15.2kg	15.9kg
Freq.Response		60Hz~15000Hz			

TK-PA Power Amplifier Series

- 100V, 70V constant voltage and 4 ~16 Ohms speaker outputs.
- 5 LED status display - Power, Clip, Signal, Protect, Temp
- Combination RCA/XLR signal inputs and outputs; short-circuit protection and alarm

Model	TK-1600	TK-2200	TK-2800	TK-3300	TK-3900
Rated Power	360W	460W	660W	1000W	1500W
Input Sensitivity	< 1200mv				
S/N Ratio	> 70db				
Freq.Response	60Hz-15KHz				
Output Mode	70V, 100V or 4~16Ω				
THD(1kHz)	< 1%				
Protection	Power turn on - turn off, High temperature, DC voltage, Short circuit limiting.				
Dimensions(H W L)	133×483×480mm				
Net Weight	14.6kg	18.5kg	19.6kg	33.8kg	38.2kg



NOTE : The Company's policy is continuous improvement of its products.
We therefore reserve the right of any deviation from illustration or specification without notice.